

# Use Manual

Voltage: AC90/240V 50-60HZ

source:10W LED\*12PCS

power: 120W

Auto. sound. master-slave, DMX512,

net weight: 4.5KG

Gross. weight: 5.25KG

packing size: 64\*46\*41cm 4pcs/Ctn (22.3KG)



Addr	A001-A512	512 Address setting
CHnd	15CH	15 channel setting
	13CH	13 channel setting
	Auto	Auto mode
SLnd	Soun	Sound mode
	SL 1	Console mode
	SL 2	Slave mode
	SH 0	Effect 0 (recommended)
SHnd	SH 1	Effect 1
	SH 2	Effect 2
	SH 3	Effect 3
	SEnS	0-99

bLAnd	bLAc	Without 512 signal, zero
	Auto	Without 512 signal, Auto
	Soun	Without 512 signal, Sound
	HoLd	Without 512 signal , maintain the status of the last console
LEd	OFF	The screen is off after 5 seconds
	ON	Screen always open
dISP	no	Display inversion
	YES	Display forward
rPAN	no	X motor forward
	YES	X motor inversion
rTiL	no	Y motor forward
	YES	Y motor inversion
REST	YES	System reset

13 channel mode

Channel	Function	Instruction
1	Horizontal operation	0-255
2	Vertical operation	0-255
3	Horizontal vertical speed	0-255
4	Dimming	0-255
5	Strobe	0-255
6	Red dimming	0-255
7	Green dimming	0-255
8	Blue dimming	0-255
9	White dimming	0-255
10	Color Auto	0-255
11	Moto Auto	0-255
12	Auto speed	0-255
13	Reset	250-255 (5 seconds)

15 channel mode

Channel	Function	Instruction
1	Horizontal operation	0-255
2	Horizontal Fine adjustment	0-255
3	Vertical operation	0-255
4	Vertical Fine adjustment	0-255
5	Horizontal vertical speed	0-255
6	Dimming	0-255
7	Strobe	0-255
8	Red dimming	0-255
9	Green dimming	0-255
10	Blue dimming	0-255
11	White dimming	0-255
12	Color Auto	0-255
13	Moto Auto	0-255
14	Auto speed	0-255
15	Reset	250-255 (5 seconds)