Use Manual



Voltage: AC 90/240V 50-60HZ
source: 10W LED*12PCS 4IN1
power: 120W
Auto,sound,master-slave,DMX512,
size:30*16.2*30.5cm
net weight:4.65KG
gross weight: 5.5KG
packing size: 56*39*39cm 2pcs/Ctn (12KG)

Addr	A001-A512	512 Address setting
CHnd	14CH	14channel setting
	11CH	11channel setting
SLnd	Auto	Auto mode
	Soun	Sound mode
	SL 1	Console mode
	SL 2	Slave mode
SHnd	SH 0	Effect 0 (recommended)
	SH 1	Effect 1
	SH 2	Effect 2
	SH 3	Effect 3
SEnS	0-99	Sound, sensitivity adjustment
bLAnd	bLAc	Without 512 signal, zero
	Auto	Without 512 signal, Auto
	Soun	Without 512 signal, Sound
	HoLd	Without 512 signal, maintain the status of the last console
LEd	OFF	The screen is off after 5 seconds
	ON	Screen always open
dISP	no	Display inversion
	YES	Display forward
rPAN	no	X motor forward
	YES	X motor inversion
rTiL	no	Y motor forward
	YES	Y motor inversion
REST	YES	System reset

11 channel mode

Channel	Function	Instruction
1	Horizontal operation	0-255
2	Vertical(1) operation	0-255
3	Vertical(2) operation	0-255
4	Horizontal vertical speed	0-255
5	Dimming	0-255
6	Strobe	0-255
7	Red dimming	0-255
8	Green dimming	0-255
9	Blue dimming	0-255
10	White dimming	0-255
11	Reset	250-255 (5 seconds)

14 channel mode

Channel	Function	Instruction
1	Horizontal operation	0-255
2	Vertical(1) operation	0-255
3	Vertical(2) operation	0-255
4	Horizontal vertical speed	0-255
5	Dimming	0-255
6	Strobe	0-255
7	Red dimming	0-255
8	Green dimming	0-255
9	Blue dimming	0-255
10	White dimming	0-255
11	Color Auto	0-255
12	Moto Auto	0-255
13	Auto speed	0-255
14	Reset	250-255 (5 seconds)